



22.18. Misc labels

This function allows you to create and save labels that you can print at any time from a label printer. Before actually printing the labels you create using this function, you must setup the printer and configure it in mSupply's setting - see the [Label printer installation](#) and [Printing preferences \(setup\)](#) section for information about this.

To access the function, choose the *Special > Misc labels* menu item. A window displaying a list of all the currently saved labels appears:



Double-click an item in the list to edit/print that label, or click the New button to add a new one. The window for adding a new label or editing an existing one looks like this (the only difference is that when editing an existing label, the window will be populated with the label's current settings):



Normal tab

This is for normal layout of printing. This will occur once per label. You can use the **quantity to print** field to specify how many time to print this same label.

Label name


This field will not print on the label, it is for you to identify the label in the list. It is shown in the list of available labels when the *Misc labels* menu item is chosen.

Heading, Body, Footers

These fields will print on the label in roughly the position that they are on the screen. Note that if you enter a very long left and right footer they may overlap in the middle of the label. Print a single test label to check first.

Multiple tab

This allows you to print the same thing multiple times on the same label:

**Layout:**

Select "2" for the same thing printed twice on the label, side by side.

Select "4" for the same thing to be printed 4 times on the label in a 2x2 grid layout.

Body:

The text you want printed on the label

Print button:

Clicking this button will print the number of labels specified in the *Quantity to print* field to your label printer using the format you have defined using the various fields.

Cancel button:

Clicking Cancel will close the window without saving any changes you have made.

OK Button:

Clicking OK will save any changes you have made and close the window. (Note that the quantity to print is not saved - it is reset to 1 each time you open the window).

Previous: [22.17. Remote authorisation](#) | | Next: [22.19. Keyboard shortcuts](#)

From:

<https://docs.msupply.org.nz/> - **mSupply documentation wiki**



Permanent link:

https://docs.msupply.org.nz/other_stuff:misc_labels?rev=1583974208

Last update: **2020/03/12 00:50**